



Workbench Notes:

Manufacturer: Arc Audio

$f(s) = 26.88 \text{ Hz}$

$Q(ts) = 0.7471$

$V(as) = 164.7 \text{ liters (5.815 cubic feet)}$

SPL = 87.37 dB SPL 1W/1m

Nominal Diam. = 0 mm (0 in.)

Spulen in Reihe

Model: Arc 15D4

$R(e) = 7.873 \text{ Ohms}$

$Q(es) = 0.9058$

Piston Diam. = 335 mm (13.19 in.)

SPL = 87.44 dB SPL 2.83 Vrms

$C(ms) = 0.151 \text{ mm/N}$

$Z(max) = 44.94 \text{ Ohms}$

$L(e) = 2.924 \text{ mH at 10kHz}$

$Q(ms) = 4.264$

BL = 18.47

$n(0) = 0.3368 \%$

$M(ms) = 232.3 \text{ grams}$

Daniels Kramladen
sypke.de

Measurements by: Treiber-Daten

Title: